

COSY™

3 DIGIT

TOKEN NUMBER DISPLAY

With Single Key Automatic Number Increment Facility.



Product Information & Operating Instructions

Model :KTD- 3DU4

Applications:

COSY Token Display System are ideal for Serving Counters in Offices, Banks, Airports, Doctors- Clinics, Restaurants and other such places where people have to wait in line for their turn. These systems allow customers to wait without having to stand in line, once their number is displayed then only they have to come to the counter for their turn.

Sounds musical chime for calling number. Option to automatically serialy increment or decrease the token numbers by pressing a single key.

Features :

- * Simple operation and easy to install.
- * Large sized 4 inches high RED LED Displays, visible from 100 feet distance.
- * Single key automatic UP /DOWN counting with pleasant musical chime.
- * Feather touch heavy duty key board.
- * Last Number remains in memory in cse of power failure.
- * Robust design. Lightweight ABS Plastic moulded control cabinets & lightweight LED displays.
- * Solid state high efficiency circuit with 8 bit micro controller.

Installation :

1. Connect the Display with main control unit by connector cable provided.
2. Connect Mains cable of console to 220 VAC . (Also Recommended 12 Volt Battery or UPS for back-up). Switch ON the system by RED Power ON/OFF switch provided at side.
3. Select the required new number Flashing duration by keeping pressed a number key + **(B)** Key before switching ON the system. e.g. (1 + **(B)** makes number flash for 1 sec.) or (5 + **(B)** for 5 sec.)

Operation:

Manual Mode : Press any required number of up to 3 digits while watching in small display of console. Use Clear Key **(C)** if required. Press the Bell Key **(B)** to send the number in main LED display and sound the musical tone . To call the same number again just press **(B)** Key.

Auto Mode : Press any required starting number up to 3 digits in Manual mode.

Change the switch to Auto Mode . Now when any of the number key 0 to 9 is pressed , the display will show the incremented next token number . (Automatic bell also sounds with every change of number followed by flashings of number for selected duration).

To serialy decrease the numbers set slide switch to DN (DOWN) postion.

Pressing the **(C)** key will also decrease the number by one.

Caution :

Do not connect or remove the connector cable of display while the system is ON.

If required use UPS or 12V battery for backup .

Specifications:

Power Supply : 220 Volts AC \pm 10% Or 12 V 7.5AH DC Battery for Backup) system has built-in battery charger.

Dimensions & Weight : **Display Units:** 12 inches X 7 inches X 1 inches X 600 gms appx.

Control Unit: 7 inches X 6.5inches X 2.5 inches x 1Kg appx.

Connecting cable : 4 core cable with 9 pin D connectors. Standard cable length provided is 10 meters.

Maximum recommended cable length 30 meters.

Manufactured by:

COSY COMMUNICATIONS , 1, Indraprastha, Sewla, Majra, Dehradun - 248 171

Tele: 0135-2640816 E-Mail: cosycom@gmail.com , Web : www.cosycom.com

ISO 9001:2000 Certified