

PROGRAMMABLE DAILY TIMER TWO SETTINGS , CONTINUOUS USE



This is a very useful device to automatically switch ON and OFF any electrical appliance or lights etc. at preset times. Simply connect the appliance or lights to be controlled in the electrical Mains socket of device. Program the timer as required . The system will automatically start switching the appliance ON and OFF at set times. Built in 4 digit LED clock with internal battery backup. Clock can be set in 24 hour time mode. The device is very compact , elegantly designed and can be easily installed . Saves Electricity and increases life of appliances by running them only for exact required periods only.

Ideal For : Automatically operating electrical appliances , lights or alarms etc. at preset times. Very use full for controlling water lifting pumps , Outdoor lights control , Neon lights control , various process controls in production and many other such timer applications .Also recommended for appliances or light etc. installed at remote locations which requires manpower and transportation expenses to switch them ON and OFF daily or on regular intervals i.e. road side signboard lighting , sirens , pump sets , street lights etc.

OPERATION :

CLOCK TIME SETTING :

Set the clock to 24 Hour mode .

Simultaneously press TIME SET button and any button H+ ,H- , M+ or M- to set the time .

TIMER SETTING :

Set the clock to 24 Hour mode . Simultaneously press ON TIME and any button H+ ,H- , M+ or M- to set the ON time . Similarly set the OFF TIME.

It is possible to set two ON times & two OFF times on daily 24 hour based clock .

IMPORTANT : Always set the time & timer settings in 24 hour mode .

AUTO FUNCTION :

Keep the switch in AUTO FUNCTION ON position to automatically Switch ON & Switch OFF the appliance at set times.

To start the appliance manually switch OFF Auto Function & use power socket switch to control the appliance manually .

For time keeping clock is installed with a Ni-cd battery type CR2032 .It may be required to replace this battery after about 2 years of use . After replacing battery keep pressed TIME SET button before switching on the power to timer .Clock will reset to 00:00.

If required use the device with suitable uninterrupted power supply ,otherwise it will not switch on the appliance automatically during on time if power fails at set on time.

Specifications :

Power : 220VAC -50 Hz

Relay contact : 10 Amp ,Max. Load 1500 watts

Clock : 4 digit LED clock, 24 Hour Mode

Clock accuracy : appx 2 minutes per month or better .

Cabinet Dimensions: 10 inches x 3 inches x 2.5 inches , ABS Molded cabinet ,