

99 Minutes Continuous ON- OFF Programmable timer



This timer allows to automatically switch ON & switch OFF electrical appliances of up to 1500 watts for preset intervals . It is possible to set any time between 1 second to 99 minutes 59 seconds.

Very use full for various domestic & industrial machinery controls ,for automatic college bells, automatic water sprinklers and many other such timer applications where separate ON time and OFF time settings are desirable repeatedly .

OPERATING INSTRUCTIONS

Connect the Load in power socket of Timer . Plug -in the power plug of timer to 220V AC.
Keep the power socket of timer connected to load in OFF position.

Switch ON the timer .

Select AUTO START or MANUAL START mode. (in AUTO Mode timer automatically starts when power is switched on).
Select AUTO REPEAT ON or AUTO REPEAT OFF mode .(AUTO repeat will continuously run the timer)

Push RESET button to clear old memory of ON TIME & OFF TIME.

Select the small RED switch to ON TIME position & Set ON TIME duration by M+ , S+ buttons .

Select the small RED switch to OFF TIME position & Set OFF TIME duration by M+ , S+ buttons .

It is possible to set any time between 1 sec to 99 Minute 59 seconds.(00:01 to 99:59)

Now switch on the power socket of timer connected to load.

Press START button once to start the timer . To pause the timer at any time press the same button again.

To operate the appliance manually switch the timer OFF and use only power socket switch .

Specifications:

Power : 220 volts AC ,50 Hz , **Max. Load :** 1500 watts

Clock Display : 4 Digit in 1/2 Inches high Red LED characters

Dimensions : 10 inches x 3 inches x 2.5 inches in ABS cabinet

Specifications and above shown design subject to changes without notice to accommodate our continuous technology upgradation.

Mfd. By : COSY COMMUNICATIONS 1, Indraprastha, Sewla, Majra, Dehradun - 248 171 (INDIA)

Tele : +91-135- 2640816 **E-Mail :** cosycom@gmail.com , **Website :** www.cosycommunications.com