

COSY™

6 DIGIT LED CLOCK

with 99 Minutes Stop Watch



Model :
6DGSW4RF

Features :

- ★ Attractive 4" High bright RED LED Characters > visible from more than 60 feet distance. (HH:MM in 4 inches and SS are shown in 2.3 inches high digits) Indoor Use only.
- ★ Selectable 12 or 24 Hour Display Format.
- ★ 99 minutes stopwatch function . MM:SS:SS (Minute : Seconds: 10th and 100th of seconds)
- ★ Internal Battery backup maintains time during a power failure , the clock will start to display accurate time as soon as the power is restored.
- ★ Sturdy black aluminum frame .
- ★ Simple push buttons to set time and control Stop watch.

Operating Instructions

TIME SETTING :

Set the clock to 24 Hour mode .

Simultaneously Keep pressed **TIME** button and any button **H+** , **H-** , **M+**, **M-** to change the time .

ALARM SETTING :

Set the clock to 24 Hour mode .

Simultaneously Keep pressed **ALARM** button and any button **H+** , **H-** , **M+**, **M-** to set the required alarm the time .

STOP WATCH MODE : (Single push button to control stop watch & clock)

Keep Pressed **STOPWATCH** button for more than 2 seconds, the clock will start showing 00:00 00 . Press **STOPWATCH** button again momentarily to start the stopwatch , pressing the **STOPWATCH** button again will stop the stop watch and pressing the same button again will reset the stop watch back to 00:00 00 .

To reach in clock mode keep pressed the same button for 2 seconds and then release .

Use External Switch port to connect an external push switch for **STOPWATCH** button to control clock /Stop watch from a distance as above..

Specifications :

Dimensions & weight : 56 cm x 15cm x 6.5cm x 2 kg appx.

Enclosure : Aluminum frame with black powder coating.

Clock accuracy : 2 minutes per month or better . 10 years built-in Lith. battery backup RTC .

Power : 100V-240V AC operation for international use.

Provision to connect 12 volt DC supply. Power consumption is only 10 Watts .

(Ideal for use in Automobiles , Ships etc. and outdoor locations)

Table and wall mounting use.

Recommended for : Large Homes ,Offices, Shops, Hotels & Restaurants, Sports and Fitness Centers, Labs , Schools ,Factories, Automobiles , Ships etc .

Manufactured by:

COSY COMMUNICATIONS , 1, Indraprastha Enclave , Sewla, Majra, Dehradun - 248 171 (INDIA)

Tele:91-135-2640816 E-Mail: cosycom@gmail.com , Web : www.cosycom.com

ISO 9001:2008 Certified Co.